


F Series (without channel)



Номер подшипника	Размеры					Chamfer(min) (rs)	Базовая нагрузка		Ограничение скорости (X1000 об/мин)		Steel ball		Вес (кг)
	d:	D:	d1	D1	H		Кр(Н)	Кукуруза)	Смазка	Масло	Number	Diameter	
F2-6	2mm	6mm	3mm	6mm	2mm	0.1	117	83	16	13	6	1	0.6
F2x-7	2.5mm	7mm	3.5mm	7mm	2.5mm	0.1	156	117	15	12	6	1.2	0.9
F3-8	3mm	8mm	3.5mm	7.8mm	3.2mm	0.1	600	480	11	15	6	1.588	0.6
F4-9	4mm	9mm	4mm	8.8mm	4.2mm	0.15	800	520	8	12	6	1.588	1.5
F4-10	4mm	10mm	4mm	9.8mm	4.2mm	0.15	658	580	6	10	6	1.588	2
F5-11	5mm	11mm	4.5mm	10.8mm	5.2mm	0.15	988	880	5	8	7	1.588	2.4
F6-12	6mm	12mm	4.5mm	11.8mm	6.2mm	0.15	1600	1255	5	7	8	2	2.5
F7-15	7mm	15mm	5mm	14.8mm	7.2mm	0.2	2200	2000	3.6	7.1	8	2.5	4.4
F8-16	8mm	16mm	5mm	15.8mm	8.2mm	0.2	2500	3000	4	8	9	3	5
F10-18	10mm	18mm	5.5mm	17.8mm	10.2mm	0.2	2230	2721	2.5	4.5	10	2.381	6